

# HDMI SWITCH

4K HDMI 16x1 multi-viewer



## OVERVIEW

HDMI 16x1 Multi-viewer is a high performance with 16 HD screen segmentation and seamless switching output. It can display 16 HD digital video signal on the same screen, and has a variety of video segmentation, seamless switching 16 HD input signal synchronously.


The control methods of the switch is flexible, it can be switched via button and IR control. It's a very practical and stable switch and easy to install, can be used in the major projects, meeting halls and other places.



## FEATURE


- Support 16 HDMI inputs, one HDMI output;
- Support 16 HDMI signal screen segmentation;
- Support 16 HDMI signal seamless switching;
- Support IR remote control;

## APPLICATIONS



Step 1 : Connecting HDMI OUT with displayer, HDMI input 1~16 with source;

Step 2 : Connecting power, and turn on the Multi-viewer .



Game



Security monitoring



Pub

## SPECIFICATIONS

HDMI input resolution	up to 1080P/60Hz
HDMI output resolution	up to 4K/30Hz
Input and output cable distance	≤10M AWG26 HDMI standard cable
Power adapter format	Input: AC (50HZ, 60HZ) 100V-240V; Output: DC12V/2A
Operating Temperature range	(-15°C to +55°C )
Dimension (L x W x H)	460x150x40 (mm)
Weight	1683g


## THE INSTRUCTION OF REMOTE CONTROL BUTTON



- 1080P** HDMI output resolution 1080P;
  - Output resolution switch(4K/1080P/2560X1440/2560X1600);
  - Vertical dual image display mode ;
  - Paralleled dual image display mode;
  - 4 big -12 small display mode;
  - 2 big -6 small display mode;
  - Audio switching; Display mode switching;
  - 16 Image display mode;
  - Left & right switching input port
  - 1** --- **16** Single image choosing signal input port
- 2x2 mode:**  
 A4: Choosing 1-4 input port signal;  
 B4: Choosing 5-8 input port signal;  
 C4: Choosing 9-12 input port signal;  
 D4: Choosing 13-16 input port signal;

**2x4 mode**  
 A8: Choosing 1-8 input port signal;  
 B8: Choosing 9-16 input port signal;

**2x4 mode without stretcher strain**  
 A8: Choosing 1-8 input port signal;  
 B8: Choosing 9-16 input port signal;



## ORDER INFOMATION

PRODUCT	PART NUMBER
4K HDMI 16x1 multi- viewer	MD-4KHDMV-1601