

HDMI SWITCH

HDMI 6x1 multi-viewer with KVM




OVERVIEW

4K 6x1 HDMI Multi-viewer is a high performance product with six HD screen segmentation and seamless switching output. It can display 6 HD digital video signal on the same screen, and has a variety of video segmentation, seamless switching 6 HD input signal synchronously. The control methods is flexible, it can be switched via button, RS232 and IR control. It's a very practical and stable product and easy to install, can be used in the major projects, meeting halls and other places.

FEATURE

- Support 6 HDMI inputs, one HDMI output
- Support 6 HDMI signal screen segmentation
- Support 6 HDMI signal seamless switching
- Support a variety of video segmentation (PIP/POP/PBP/Single image/ Dual image/Four image ect) ; Each screen segmentation can move freely/expand/shrink/rotate 180 degree (put mouse on the top left of image can expand or shrink ; Click the top right of image can acheive rotate) ; Click the mouse on the bottom right corner of the screen to switch the sound ON/OFF
- Support touch screen
- Support IR /Button/RS232 control
- Support audio and video superposition
- More clearer subtitles

APPLICATIONS



Game



Security monitoring



Pub

FOCOMM (THAILAND) CO., LTD

12 Soi Sukhaphiban 5 Soi 5 Yaek 3, Tha Raeng Subdistrict, Bang Khen District Bangkok 10220


Email : info@focomm-cabling.com www.focomm-cabling.com



SPECIFICATIONS

HDMI Input resolution	Max 3840x2160/30Hz
HDMI output resolution	Max 3840x2160/60Hz
Audio format	Stereo
Input cable distance	≤8m AWG26 HDMI standard cable
Output cable distance	≤10m AWG26 HDMI standard cable
Max working current	1.4A
Power adapter format	Input AC (50HZ, 60HZ) 100V-240V; Output: DC12V/2A
Operating Temperature range	(-10°C to +45°C)
Dimension (L x W x H)	263x159x38(mm)
Weight	1272g

OPERATION INSTRUCTION



Segmentation mode button

: Six image mode

: Four image mode

: Vertical three image mode A:In1-3; B:In4-6

: Horizontal three image mode A:In1-3; B:In4-6

: One big -Two small display mode A:In1-3; B:In4-6

: Vertical two image mode A:In1-2; B:In3-4 C:In5-6

: Horizontal three image mode A:In1-2; B:In3-4 C:In5-6

: One big -Four small display mode

Single image display mode

1 --- Input1

2 --- Input2

3 --- Input3

4 --- Input4

5 --- Input5

6 --- Input6

Keyboard (Single image display mode)

1 --- Input1

2 --- Input2

3 --- Input3

4 --- Input4

5 --- Input5

6 --- Input6

: Audio switch

: Mode switch

ORDER INFORMATION

PRODUCT	PART NUMBER
HDMI 6x1 multi-viewer with KVM	MD-HDMV-KVM-0601